

# BC-100 Wireless Boundary Microphone

## Key Features

- BC-100 can be installed with MIPRO ACT-30T, ACT-50T, ACT-70T or ACT-80T wireless bodypack transmitter into a wired or wireless boundary microphone or gooseneck (with either the MM-202 or MM-202B gooseneck mic).
- Back panel has a balanced XLR connector with switch for external gooseneck or wireless boundary microphone option.
- Built-in electret condenser for excellent sensitivity and clear boundary microphone use.
- Simply plug the mini XLR into a MIPRO bodypack transmitter connector and insert the transmitter into the back slot for an easy to use wireless conference system.
- Push-to-Talk/Mute button provides easy speaking or mute option.
- Ideal solution for boardrooms, conference centers, schools, government, houses of worship and other installed sound applications.






## Transmitters & Microphones

<b>ACT-30T</b>	Bodypack Transmitter
<b>ACT-50T</b>	Bodypack Transmitter
<b>MM-202</b>	Gooseneck Microphone
<b>MM-202A</b>	Gooseneck Microphone
<b>MM-202B</b>	Gooseneck Microphone
<b>MM-202S</b>	Gooseneck Microphone

## Technical Specifications

Built-in Microphone	Input Microphone Sensitivity : 50 Hz~20 kHz, Uni-directional (hypercardioid) Frequency Response : 50 Hz~20 kHz Maximum SPL : 132 dB SPL (1% T.H.D@1 kHz)
Power Supply	5V DC (via built-in transmitter)
Current Consumption	< 1.0mA
Input Connector	Mini TA4F XLR-4pin (male) x1
Output Connector	Balanced XLR
TALK/MUTE Button	Mechanical PUSH-HOLD switch
Color	Black
Dimensions	100(W)x55(H)x150(D)mm / 4.0(W)x2.2(H)x6.0(D)"
Weight	Approx. 170g / 6oz



MIPRO Electronics Co., Ltd

Headquarters: 814 Pei-kang Road, Chiayi, 60096, Taiwan  
Tel: +886.5.238.0809 | Fax: +886.5.238.0803  
www.mipro.com.tw | mipro@mipro.com.tw